

## Description

The AW-D319 Addressable I/O Module (AW-D319 for short) is used with AW-FP300 fire alarm control panel. It is mainly used to realize an output control for fire linkage equipment (such as smoke dampers, blow valves and fire dampers) and receive the feedback signals of the fire linkage equipment so that a judgment on whether or not the fire linkage equipment is operating normally can be done.



## Technical Specification

<b>Executive Standard</b>	EN54-18
<b>Operating Voltage</b>	Signal Loop 24V(18V~28V) Power 24VDC(20VDC~28VDC)
<b>Standby Current</b>	Loop<0.8mA ; Power<2mA
<b>Action Current</b>	Loop<5mA ; Power<15mA
<b>Output Capacity</b>	1A@DC30V
<b>Input Mode Setting</b>	NC or NO input mode can be set by the jumper JP4
<b>Programming Method</b>	Electronically addressed
<b>Code Range</b>	One address within 1~324
<b>Indicators</b>	Inspection indicator: 1 blink once about every 12 seconds in the inspection status or remain lit in the output status Input indicator: remain lit in the feedback status
<b>Operating Temperature</b>	-10℃~+55℃
<b>Relative Humidity</b>	≤95%, non-condensing RH: ≤95% (40℃±2℃, without condensation)
<b>Material of Enclosure</b>	ABS
<b>Dimension</b>	86mm×86mm×41mm (L×W×H) (with base)
<b>Mounting Hole Distance</b>	60.5mm
<b>Weight</b>	About 148g (with base)